

teeth Poles	3	6	9	12	15	18	reduction
2	ABC	ABCabc	AacBBaCCb	AAccBBaaCCbb	AAACCbbbaaCCCbb	AAAcccBBBaaaCCCbbb	1
4	ABC	ABCABC	ABaCAcBCb	AcBaCbAcBaCb	AAcBaCCbAcBBaCb	AAcBBaCCbAAcBBaCCb	2
6			ABCABCABC			AcBaCbAcBaCbAcBaCb	3
8	ABC	ABCABC	AaABbBCcC	ABCABCABCABC	AcaCABabABCbcBc	ABaCAcBCbABaCacBCb	4
10	ABC	AbCaBc	AaABbBCcC	AabBCcaABbcC A-b-C-a-B-c	ABCABCABCABCABC	AcabABCbcaCABabcBC	5
12			ABCABCABC			ABCABCABCABCABC AaBbCcAaBbCcAaBbCc A-B-C-A-B-C-A-B-C	6
14	ABC	AcBaCb	ACaBAbCBc	AacCBbaACcbB A-b-C-a-B-c	AaAaABbBbBCcCcC	AabcCABbcaABCcabBC	7
16	ABC	ABCABC	AAbCCaBBc	ABCABCABCABC	AaAaACcCcCBbBbB	AaABbBCcCAaABbBCcC	8
20						AaABbBCcCAaABbBCcC	10

Wyjaśnienie:

poziomo oznaczenie ilości zębów, pionowo magnesów.

Niebieski - Dobra kombinacja

Biały - Działa

Czerwony - Działa ale kiepsko

Czarny - wcale nie działa

Litery ABC to fazy,

A(duże litery) - nawinięcie CW - zgodnie z ruchem wskazówek zegara.

a(małe litery) - CCW - w drugą stronę.

minus to puste ramię.

Grooves Pole	3	6	9	12	15	18	Spin factor
2	ABC	Abcabc	AacBBaCCb	AAccBBaaCCbb	AAACCbbbaaCCCbb	AAAcccBBBaaaCCcbbb	1
4	ABC	ABCABC	ABaCacBCb (For speed)	AcBaCbAcBaCb	AAcBaCCbAcBBaCb (For speed)	AAcBBaCCbAAcBBaCCb	2
6			Abcabcabc (For speed)			AcBaCbAcBaCbAcBaCb	3
8	ABC	ABCABC	AaABbBCcC	ABCABCABCABC (For speed)	AcaCABabABCbcBc	ABaCacBCbABaCacBCb (For speed)	4
10	ABC	Abcabc	AaABbBCcC	AabBCcaABbcC Abcabc	ABCABCABCABCABC	AcabABCbcaCABabcBC	5
12			Abcabcabc			ABCABCABCABCABC AaBbCcAaBbCcAaBbCc Abcabcabc	6
14	ABC	AcBaCb	ACaBAbCBc	AacCBbaACcbB Abcabc	AaAaABbBbBCcCcC	AabcCABbcaABCcabBC	7
16	ABC	ABCABC	AAbCCaBBc	ABCABCABCABC	AaAaACcCcCBbBbB	AaABbBCcCAaABbBCcC	8
18							9
20	ABC	ABCABC	AbbCaaBcc	AbCaBcAbCaBc	ABCABCABCABCABC	AaABbBCcCAaABbBCcC	10

[www.powercroco.de](http://www.powercroco.de)